

# TAKTIS FIRE

## Additional Boards 8-Way Sounder

### Features

- ▶ Simple 'plug-in' connection to the Taktis Control Panel
- ▶ 4 sounder outputs
- ▶ Fault and operated LED on board indicators
- ▶ Decals provided to redesignate Taktis terminals



### Description

To further enhance the versatility of the Taktis Control Panel, additional sounder output capability can be added using Sounder Boards.

Each board have 4 monitored sounder outputs, which can be individually programmed.

### Specification

Product Code	K793
Supply Voltage	21 - 30V DC
End of line resistor value	Diode (1N4001)
Quiescent current consumption	30mA
Full alarm current consumption	50mA (exclude current draw on sounder outputs)
Current per sounder output	2.5A per channel
PCB size	62.8mm x 234.6mm
Cable capacity	2.5mm <sup>2</sup> per terminal (Taktis main/extender board)
Operating temperature	-5°C to +40°C (±2°C)
Operating humidity	<95% (non-condensing)
Configuration	4 x class "B", or 2 x class "A"

For full technical and application details see the Taktis Additional Boards Installation Manual. Kenetc Ref. Man-1170EN.