

# K-Mesh

## Wireless Fire Detection

### KM-WL8-OS

#### Wireless Optical Smoke Sensor with Sounder

#### Features

- ▶ Approved to EN54-3, 7 & 25
- ▶ RED compliant
- ▶ Sounder incorporated
- ▶ 6selectable tone modes
- ▶ Internal algorithm processing for optimal performance
- ▶ Tamper switch
- ▶ Up to 10 years battery life\*
- ▶ Utilises standard low cost lithium battery technology
- ▶ Bi-directional wireless communications
- ▶ Self-optimising wireless amplitude and frequency
- ▶ Compatible with all K-Mesh Translator/Expander modules

#### Description

The KM-WL8-OS Optical Smoke Sensor with Sounder is the latest in wireless smoke sensor technology. A fully intelligent device compatible with the K-Mesh Translator and Expander modules.

K-MESH wireless smoke detectors contain advanced internal algorithms to ensure they continuously operate at their optimal performance.

Three configurable sensitivity levels are provided for the smoke element - Low, Normal, High, these can be configured through the K-Mesh Wireless Translator screen or via the K-Mesh configuration software.

The sounder element is configurable independent of the sensor and can be configured in the panel cause and effect the same as a standard addressable sounder. Two operational frequencies are provided in the sounder along with 6 selectable tone modes which can be programmed via the K-Mesh Translator. KM-WL8-OS has a maximum sound output of 96dB(A) at 1m.

Well proven adaptive radio signal processing algorithms are used within the device along with self-optimising wireless amplitude and frequency technology provide the highest levels of life safety and system reliability.



The Wireless Smoke Sensor is provided with the mounting base, complete with a built in anti-tamper switch which will indicate a fault at the panel should the device be removed from its associated detector base. An LED indication is provided on the top of the detector which is visible through 360°, this will flash green in standby mode, flashes yellow in fault and flashes red in an alarm condition providing clear indication of the device status.

The detector can be programmed to turn off the flashing green and flashing yellow LED status, to preserve battery life. In this instance the status LED will only be used to indicate a fire state.

An in-built magnet test feature enables easy activation of the device to verify functionality and response.

Primary and secondary batteries are fully monitored with low battery voltages being displayed on the Kentec Fire Alarm Control Panel.

#### Ordering codes

Part no.	Description
KM-WL8-OS	Wireless Optical Smoke Sensor with Sounder

#### Standards & Approvals

EN 54-3 Sounders

EN54-25 Components using radio links

EN 54-7 Smoke Detectors



Specifications		
Operating frequency range	866 - 869.85 MHz	
Communication range (in open air)	1200 m	
Modulation type	GFSK	
Operating frequency channels	6	
Max. radiated power	≤ 25 mW	
Sound pressure level	Max 96 dB(A) at 1m for all modes	
Tone frequencies (Hz)	Tone 1 - 3500	
	Tone 2 - 2150	
Tone modes	One tone continuous - Tone 1	
	One tone intermittent - Tone 1 (1s on/1s off)	
	One tone intermittent - Tone 1 (2s on/2s off)	
	Dual tone - Tone 1 + Tone 2 (1s/1s)	
	Dual tone - Tone 1 + Tone 2 (0.4s/0.4s)	
	One tone intermittent - Tone 1 (0.2s on/1.3s off)	
Operating temperature range	- 10 °C to + 55 °C	
Max. tolerated humidity	95% RH (non condensing)	
Dimensions (mm)	Ø 111 x H 65	
Weight (g)	200	
Power supply (Dual 3V lithium batteries)	1 x Primary cell (CR123A)	1 x Secondary cell (CR123A)
	1.2 Ahr	1.2 Ahr
	8 - 10 years primary battery life*	3 months secondary battery life

\*Dependent on operational usage

Datasheet DS177 11/21 Rev.01

For further information visit [www.kentec.co.uk](http://www.kentec.co.uk)

Kentec Electronics Ltd. reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Kentec Electronics Ltd. to be a complete and up-to-date description.